

MF

MAINTENANCE FREE

Supplied with an acid pack, MF batteries (AGM technology) must be activated by filling the acid before the first use. Totally sealed once activated, the gas recombination technology doesn't require maintenance or any water refiling.

ORIGINAL EQUIPMENT
OEM
MANUFACTURER



TO BE ACTIVATED

AGM (Absorbent Glass Mat) technology.



ACID PACK INCLUDED

For initial filling.



NO MAINTENANCE*

VRLA (Valve Regulated Lead Acid) design.



TIGHTLY SEALED AFTER FILLING

Electrolyte is held in a glass fiber mat.



SUPERIOR POWER & EXTENDED CYCLE LIFE



LONG SHELF LIFE


No need to be recharged while stocked (if not activated).



*once activated

MOUNTING ANGLES

MEDIUM INCLINATION



COMPATIBLE CHARGERS

BS 10
Battery size up to 20Ah

BS 15
Battery size up to 30Ah

BS 30
Battery size up to 60Ah

BS 60
Battery size up to 120Ah

BK 20
Battery size up to 40Ah

DID YOU KNOW?

MF batteries are not suitable for e-commerce. Since February 1st, 2021, the regulation (EU) 2019/1148 prohibits the sale of acid batteries to the public in Europe.

BS in MF battery type means Bottle Supplies.

BS BATTERY TYPE	BS CODE	CAPACITY Ah (10Hr)	CAPACITY Ah (20Hr)	CCA A (-18°C)	DIMENSIONS (±2mm)			ASSEMBLY LAYOUT	TERMINAL
					L	W	H		
BT4B-BS	300625	2.3	2.4	40	113	38	85		J
BTR4A-BS	300624	2.3	2.4	45	113	48	85		I
BTX4L-BS	300909	3	3.2	50	113	70	85		A
BT5AL-BS	300747	5	5.3	65	120	60	130		B
BTX4L-BS+/BTZ5S-BS	300617	4	4.2	50	113	70	85		A
BTX5L-BS	300618	4	4.2	80	113	70	105		A
BTZ7S-BS	300695	6	6.3	130	113	70	105		A
BTX7A-BS	300619	6	6.3	105	150	87	93		A
BTX7L-BS	300620	6	6.3	100	113	70	130		A
BT7B-BS	300626	6.5	6.8	85	150	65	93		A
BT9B-BS	300627	8	8.4	120	150	70	105		A
BTX9-BS	300621	8	8.4	135	150	87	105		A
BTZ10S-BS	300696	8.6	9	190	150	88	93		A
BT9A-BS	300748	9	9.5	115	135	75	139		A
BT12A-BS	300602	10	10.5	175	150	88	105		A
BT12B-BS	300628	10	10.5	210	150	70	130		A
BTX12-BS	300603	10	10.5	180	150	87	130		A
BTZ12S-BS	300697	11	11.6	215	150	88	110		A
BT14B-BS	300629	12	12.6	210	150	69	145		A
BTX14-BS	300604	12	12.6	200	150	87	145		A
BTX14L-BS	300605	12	12.6	200	150	87	145		A
BTX14AH-BS	300606	12	12.6	210	133	90	164		A
BTX14AHL-BS	300607	12	12.6	210	133	90	164		A
BTZ14S-BS	300698	11.2	11.8	230	150	88	110		A
BTX16-BS	300609	14	14.7	230	150	87	161		A
BTX16-BS-1	300623	14	14.7	230	150	87	161		E
BTX20-BS	300611	18	18.9	270	175	87	155		A
BTX20A-BS	300808	18	18.9	270	150	87	161		A
BTX20CH-BS	300616	18	18.9	270	150	87	161		A
BTX20L-BS	300610	18	18.9	270	175	87	155		A
BTX20HL-BS	300614	18	18.9	310	175	87	155		A
BTX20H-BS	300613	18	18.9	310	175	87	155		A
BTX24HL-BS	300630	21	22.1	350	205	87	162		A
BIX30L-BS	300753	30	31.6	400	168	126	173		A

12V

TERMINAL TYPE	A	B	C	D	E	F	G	H	I	J